

86" KTA



Feature

- **Front Speaker 15w x 15w**
- **Front OSD**
- **Front HDMI/ Touch signal input**
- **Front USB input signal**
- **AG glass 4mm**
- **Built-in android system and wireless ap**

Specification

Model	86KTA
Dimensions	2025mm(L) x1214mm(H) x 105mm (T)
Display area	1897mm(H) x1067mm(V)
Contrast	4000:1
Resolution	3840 x 2160 (UHD)
Pixel	0.1625mm x 0.4875mm
Response time	6.5ms
Brightness	370 cd/m2
Power input	100~240VAC, 50/60Hz
Power consumption	<380W
Front input	15W*2, USB Type A*1, USB Type B*1, HDMI*1, VGA*1, Mic*1, , IR Receiver, Front Button
Input connector	DP*1, HDMI*6 (Front*1, Built-in*2, Side *2, Under*1), USB2.0*5 (Built-in*3 (Type A*2+Type B*1),Front*2 (Type A*1 + Type B*1),

	USB3.0 Type A*2 , YPbPr*1, RJ45*1, SPDIF*1, VGA in *1, AV*1, Audio in *1, USB Touch*2 (Front*1), RS232*1, WIFI*2, Earphone*1, Built-in 4K OPS
Output connector	Left/Right Speaker, RJ45*1, HDMI*1, Audio out*1
Android version	5.1 version; RAM: 2G, Rom: 8G
Wireless Access Point	Built-in 5G Wireless Access Point support 802.11 ac (2.4GHz & 5GHz dual band)
USB player format	MP3, WAV, APE, FLAC, AAC, OGG, 3GPP, WMA, M4A
USB Touch signal	Can use touch function to control signal input source. No need to use remote control
Firmware function	Built-in electrical whiteboard, clock, calendar, weather, internet, screen mirroring, Wireless access point
Viewing Angle	178/178
Screen control	Remote control & OSD&RS232&Touch
Tempered glass	4mm tempered glass
Speaker	15W*2
Touch driver	Plug & play without install any driver 10 points touch
Touch mode	Finger, pen or any object larger than 5mm
Screen Unique Function	Quick customize app button
Touch resolution	32767 x 32767
Touch limited	Unlimited
Backlight life	50,000hr
Touch speed	>100 frame / sec (faster touch)
Temperature / Humidity	Storage : -20°C ~60°C/10% ~ 90% , Work : -5°C -60°C/10% ~ 90%
OS support	WIN XP, 7, 8, 10, Android and Mac
Weight	79KG